



WallPod EV: HomeCharge

Surface / Post Mount Version
With Tethered Lead

CONTENTS

- WallPod EV Deep Base Unit
- WallPod EV Tethered Lead and Plug (pre fitted)
- WallPod Cable Management Bracket

INSTALLATION INSTRUCTIONS

It is recommended that this WallPod EV: HomeCharge unit be installed by a competent electrician in accordance with BS7671 and the IET Code of Practice

1. Check the contents of the carton ensuring that the unit is undamaged.
2. Establish a suitable location for mounting the WallPod unit in association with the electric vehicle's parked charging location. Remember to allow room for the cable and its bracket which will need a further 80mm above the unit.
3. Remove the WallPod from its protective packaging.
4. Using a screwdriver, remove the WallPod's front cover by removing the 6x screws located in the cover that attach to the base unit, taking care to place the screws in a safe place.
5. Carefully drill out a hole in each of the four raised oval mounting lugs situated in the base unit to suit the size of your intended fixing bolts or screws.
6. Holding the WallPod in its desired final position, mark the four fixing holes by inserting a marker pencil through the base unit's drilled holes onto the intended mounting surface.
7. Establish where you wish the supply/earth cable to enter the unit, and drill out the hole to accept the appropriate cable gland(s) Please note that the top cable entry recess cannot be used if the cable management bracket is to be fitted.
8. Using the marks made in the wall, mount the WallPod unit ensuring that the cable management plate is slotted over the top two mounting lugs on the rear of the base unit and screw or bolt into place giving consideration to the use of washers to seal.
9. Connect the supply/earth cable in accordance with BS7671 and the IET Code of Practice.
10. On completion of electrical connections, check all other terminations and test.
11. Carefully refit the front cover to the base unit taking care to align the switchgear and the access pod, whilst ensuring that the cover is properly fitted to the base unit and secured with the 6x fixing screws provided.
12. Coil the lead around and over the WallPod using the cable management bracket stowing the lead in the socket.
13. The unit is now ready to use.

EUROPEAN LOW VOLTAGE DIRECTIVE NOTICE

This unit is not intended for use by persons (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety. Children should be supervised to ensure they don't play with the unit.

MAINTENANCE

The WallPod is designed to give you years of trouble free service. The life of the WallPod will be enhanced if the following are observed:

- The exterior of the WallPod can be cleaned with a soft damp cloth. Mild detergent can be used on heavily soiled areas.
- DO NOT use any solvents or oils to clean the WallPod.

• **Please recycle this product whenever possible.**

• **Not to be discarded with household waste.**



Tel: 01205 724754

Email: rolec@rolecserv.co.uk

Web: www.rolecserv.com